K3A100 10kN/10kN/20kN



Description

The K3A 3-axis sensor is designed for measuring force in three mutually perpendicular axes. This product group has a wide measurement ranges for the forces. The K3A S3-Axis Force Sensors are developed for the following applications:

- 1. Robotics,
- 2. Medical technology,
- Measurements in automation technology,
- 4. Mounting and Assembling of Parts in Production Lines,
- 5. 6-Axis Force/Torque Platforms consisting of 4x K3A Sensors,
- 6. Research and Testing.

The calibration document contains the individual calibration factors and crosstalk data of the sensor. The crosstalk optionally can be minimized by application af an additional error compensation matrix. The K3A sensors can be operated without additional compensation matrix.

During the application, please take care to ensure that the maximum bending moments are not exceeded. The lever arms are calculated from the sensor origin, which is in the center of the mounting surface (on the top surface).

Technical Data

Force sensor Туре 3-axis force sensor Tension / Compression Force direction Rated force Fx 10 kΝ Rated force Fy 10 kΝ Rated force Fz 20 kΝ Inner thread Force introduction Dimension 1 8xM10x1.5 Sensor Fastening Inner thread Dimension 2 8xM10x1.5 Operating force 150 %FS Material Stainless steel Height 72 mm Length or Diameter 100 mm Torque limit 1.5 kNm Bending moment limit 0.5 kNm

Precision

Accuracy class	0,2%	
Relative linearity error	0.2	%FS
Temperature effect on zero signal	0.01	%FS/K
Temperature effect on characteristic value	0.01	%RD/K
Relative creep	0.01	%FS

Connection Data

Connection type	Connector
Name of the connection	integrated round plug connector MP11, 24-pole, male

Eccentricity and Crosstalk

Crosstalk from x to y at rated load	2 %FS
Crosstalk from y to x at rated load	2 %FS
Crosstalk from z to x/y at rated load	1 %FS
Crosstalk from x/y to z at rated load	1

Temperature

Rated temperature range f	-10 70 °C
Operating temperature range f	-10 85 °C

Electrical Data

Rated output x-axis	1.5	mV/V / FS
Rated output y-axis	1.5	mV/V / FS
Rated output z-axis	0.8	mV/V / FS
Zero signal	0.05	mV/V

Rated range of excitation voltage f	2.5 5	V
Operating range of excitation voltage f	1 10	V
Input resistance x-axis	700	Ohm
Output resistance x-axis	700	Ohm
Input resistance y-axis	700	Ohm
Output resistance y-axis	700	Ohm
Input resistance z-axis	1400	Ohm
Output resistance z-axis	1400	Ohm
Insulation resistance	5	GOhm

Abbreviation: RD: "Reading"; FS: "Full Scale"; The exact nominal sensitivity is indicated in the test report;

Pin Configuration

Symbol	Description	Wire colour	PIN
+Us	positive bridge supply	blue	2
-Us	negative bridge supply	brown	1
+Ud	positive bridge output	white	3
-Ud	negative bridge output	green	4
+Us	positive bridge supply	yellow	6
-Us	negative bridge supply	pink	5
+Ud	positive bridge output	black	7
-Ud	negative bridge output	grey	8
+Us	positive bridge supply	purple	10
-Us	negative bridge supply	red	9
+Ud	positive bridge output	grey / pink	11
-Ud	negative bridge output	red / blue	12
	+Us -Us +Ud -Ud +Us -Us +Ud -Ud +Us -Us -Us -Us +Us -Us +Us -Us +Ud	+Us positive bridge supply -Us negative bridge output +Ud positive bridge output -Ud negative bridge output +Us positive bridge supply +Us positive bridge supply -Us negative bridge output +Us positive bridge output +Us negative bridge output +Ud positive bridge output +Ud positive bridge output +Ud negative bridge output +Us positive bridge supply -Us negative bridge supply -Us negative bridge supply +Ud positive bridge supply +Ud positive bridge supply	+Uspositive bridge supplyblue-Usnegative bridge supplybrown+Udpositive bridge outputwhite-Udnegative bridge outputgreen+Uspositive bridge supplyyellow-Usnegative bridge supplypink+Udpositive bridge outputblack-Usnegative bridge outputblack+Udpositive bridge outputgrey+Udnegative bridge outputgrey+Udnegative bridge outputgrey+Uspositive bridge supplypurple-Usnegative bridge supplyred+Udpositive bridge supplyred+Udpositive bridge supplygrey / pink

Compressive load: positive output signal. Shield- transparent.

accessories

	Description	Description
	GSV-8DS	8-channel amplifier with USB port, analog output, UART interface. Other versions GSV-8AS CAN with Canbus and GSV-8AS EC with EtherCAT fieldbus.
•Ö	Connection cable MP11/f-D- Sub44HD/m/straight	Straight connection cable for connecting the K6D sensor to an 8-channel measuring amplifier GSV-8DS SubD44HD
r0	Connection cable MP11/f-D- Sub44HD/m/angled	Angled connection cable for connecting the K6D sensor to an 8-channel measuring amplifier GSV-8DS SubD44HD
	Calibration Certificate kn/20/5/K3D	Factory calibration certificate for force to 20 kN in accordance with DIN EN ISO / IEC 17025 for test materials monitoring according to DIN ISO 9001: 2008 with 5 load levels and 3 series of measurements.
.a0], _{11]}	Calibration Certificate kn/200/5/K3D	Factory calibration certificate for force from 21 kN to 200 kN in accordance with DIN EN ISO / IEC 17025 for test materials monitoring according to DIN ISO 9001: 2008 with 5 load levels and 3 series of measurements.